AcousticDesign[™] Series AD-C4T-ZB

KEY FEATURES

- Zero bezel design for the needs of modern applications
- Consistent tonal characteristics across the entire AcousticDesign Series for surface, ceiling, and pendant applications
- DMT (Directivity Matched Transition[™]) waveguide ensures smooth, uniform frequency response over the coverage area
- Snap-fit magnetic grille
- 3x double stepped, long travel dog-ear blind mount system
- Intrinsic Correction™ voicings available via the Q-SYS Platform including CX-Q amplifiers
- Blemish-free removable logo
- Removable conduit cover plate, also available as accessory for pre-install wiring
- UL1480 and UL2043 certified
- Available in white (RAL 9003)
- Complete EASE, CF2, CAD, & BIM information available online



AcousticDesign[™] Series AD-C4T-ZB

4.5" small format, zero bezel ceiling mount loudspeaker

The Q-SYS AcousticDesign[™] AD-C4T-ZB is a 4.5" two-way, zero bezel ceiling loudspeaker ideally suited for a wide variety of foreground and background sound reinforcement applications which utilize 70/100V or 16Ω bypass configurations.

The AcousticDesign[™] Series offers integrators a premium quality installed sound solution where performance, consistent coverage, and aesthetics are paramount. Specifically designed to maintain a consistent tonal characteristic across the entire family in ceiling, surface, and pendant applications, the AcousticDesign Series allows integrators seamless transitions within blended installations.

The AD-C4T-ZB features a high quality $4.5^{\prime\prime}$ weather treated paper cone woofer with a 1 $^{\prime\prime}$ voice coil and a .75 $^{\prime\prime}$ aluminum dome tweeter which is positioned on a DMT waveguide.

DMT (Directivity Matched Transition™) is Q-SYS's design philosophy where the high frequency waveguide is matched to the natural conical behavior of the woofer at the crossover point. The result is a coherent transition between transducers with improved off-axis power response for consistent 150° conical DMT coverage.

The accurate frequency response of the AD-C4T-ZB is maintained even in 70/100V applications by use of a low-loss, low-saturation 30-watt transformer with selectable taps, including 16Ω bypass, using a rotary selector located under the snap-fit magnetically attached powder coat steel grille.

To retain lasting good looks, the rugged ABS baffle is further protected by using UV inhibitors that prevent discoloration and by a powder coated steel back can. The magnetic grille features a stick-on logo that can be removed blemish-free for installations where branding is not permitted.

Installers will appreciate the 3x double stepped, long travel dog-ear blind mounting system, which captures from 0" - 2.25" of ceiling thickness. The conduit cover plate can be easily removed by losening the single captive Phillips screw allowing access to the locking 4-pole Euro-block connector which can accept up to four 18AWG pairs, eliminating the hassles of star topology wiring designs.

Intrinsic Correction[™] voicings that optimize performance and speed the install process are easily deployed via the Q-SYS Platform including CX-Q Series amplifiers.

The AD-C4T-ZB is available in white (RAL 9003) and may be painted to match any decor.

For your system integration needs, complete EASE, CF2, CAD, and BIM files are available for download at Q-SYS.com.



AD-C4T-ZB

LF transducer	114 mm (4.5 in) weather treated paper cone woofer
HF transducer	19 mm (.75 in) aluminum dome tweeter
Effective frequency range ^{1, 2, 3, 8}	70 Hz – 20 kHz
Rated noise power / voltage ⁶	30 W / 22 V (rms)
Sensitivity (dB)	Rated @1W, 1 m ^{2,3,4,8} : 87
Coverage (-6 dB) (°)	Rated ^{2, 5, 8} : 150 conical DMT
Horizontal / Vertical ⁹	500Hz: 176 / 176, 1kHz: 160 / 160 2kHz: 156 / 152, 4kHz: 103 / 111
Declared values of SPL, 1/3rd octave band CPB, 1W, 4m (Hz : dB)°	500: 59.1; 630: 59.4; 800: 60.0; 1000: 60.0 1250: 61.0; 1600: 60.5; 2000: 62.3; 2500: 61.0 3150: 58.0; 4000: 62.2
Directivity factor ^{2, 5, 8}	4.5
Directivity index (dB) ^{2, 5, 8}	6.5
Maximum SPL (dB)	Rated, 1m (continuous / peak) ⁷ : 102 / 108
Recommended amplifier	60 watts
Transformer taps / impedance	Bypass: 16 Ω 3.75 W (70 V); 7.5 W (100 V) Tap: 1333 Ω 7.5 W (70 V); 15 W (100 V) Tap: 667 Ω 15 W (70 V); 30 W (100 V) Tap: 333 Ω 30 W (70 V); N/A (100 V) Tap: 167 Ω
Input connector type	Euroblock connector with parallel output
Enclosure material	ABS baffle on powder coated steel back can
Grille material	Powder coated steel
Ingress protection	IP-34
Operating environment	Designed for indoor use
Operating temperature range	-20 to 50° C (-4 to 122° F)
Cutout dimension	Ø 195 mm (Ø 7.68 in)
Net weight	2.9 kg (6.4 lb)
Product dimensions (Ø x H)	Ø 230 x 176 mm (Ø 9.06 x 6.94 in)
Shipping weight	9.3 kg (20.5 lb), pair packed
Shipping dimensions (H x W x D)	279 x 711 x 318 mm (11 x 28 x 12.5 in), pair packed
Included accessories	C-ring and tile rails, rail screws, euroblock connector, cut-out template, grille
Optional accessories	AD-MR4 (pre-install mud ring)
Safety Agency	UL1480, UL2043, NFPA90, NFPA70 suitable for use in air handling spaces. Transformer UL registered per UL1876, ROHS, CE compliant. Baffle meets UL94-V0 and UL94-5VB flamibility rating; in accordance with IEC60849 / EN60849 systems.

¹ - 10dB from rated sensitivity ² Full-space, IEC baffle, 4m ³ Reference axis ⁴ 200 - 10kHz average ⁵ 500 - 5kHz average ⁶ IEC, 2hrs ⁷ Calculated from rated noise power and sensitivit

^a Reference plane is the plane coincident with the loudspeaker baffle plane. Reference axis is the axis perpendicular to the reference plane and passing through the center of the baffle. Vertical plane is the plane intersecting the reference plane at a right angle, including the reference axis and the taps selector knob. Horizontal plane is the plane intersecting the reference plane and the vertical plane at a right angle, including the reference axis.

AD-C4T-ZB

(dB) Level, Sound pressure Impedance, Amplitude (ohm) 100 100 95 90 80 90 70 85 60 80 75 50 70 40 65 30 60 20 55 10 0 50 20 50 100 200 500 1k 2k 5k 10k 20k Frequency (Hz) FLC: Frequency Response (Raw), 1W, 1m FLC: Frequency Response (Intrinsic Correction(tm)), 1W, 1m iFLC: SPL, 1/3rd octave band, 1W, 4m, EN54-24 eq applied iFRC: Impedance (Direct)

Impedance/Frequency Response:

Beamwidth:



Dimensions



As part of Q-SYS's ongoing commitment to product development, specifications are subject to change without notice.

0 Q-SYS

+1·800·854·4079 | +1·714·754·6175 | WWW.QSYS.COM

© 2023 QSC, LLC all rights reserved. QSC, LLC's trademarks include but are not limited to Q-SYS[™], Q-SYS logo, and all trademarks are listed under www.qsys.com/trademarks, some of which are registered in the U.S. and/or other countries. All other trademarks are the property of their respective owners. 10/30/2023